

## Instructions for Tuning your receiver to the Optus D2 Satellite

### **Topfield TF3030F**

Before you begin identify the following buttons on the remote control for the satellite receiver:- **Menu, exit, OK, the up-down and left-right buttons, and the red button.**

Switch on the satellite receiver and TV as you normally would to watch one of the channels:- now you are ready to begin:-

**Note:-** When you 'select' an item on the on-screen menu it will be a different colour to the other items

#### **To scan in the channels:-**

1. Press the **menu button** and select **Installation** with the **up or down** button and press **OK**
2. Select **SAT/TP Edit** with the **up or down** button and press **OK**
3. Select **Add new TP** and press **OK**
4. For **Frequency** type in **12706**
5. Use **down** button to select **Symbol Rate** and type in **22500**
6. Use **down** button to select **Polarization** and use **left or right** button to select **VER**
7. Use **down** button to select **OK** and press **OK**
8. Press **Menu**
9. Select **Channel Search** and press **OK**
10. Select **Search Mode** with the **up or down** button and with the **left or right** button set to **Auto**
11. Select **Network Search** with the **up or down** button and with the **left or right** button set to **On**
12. Select **FTA/Scrambled** with the **up or down** button and with the **left or button** set to **FTA Only**
13. Select **Start Search** with the **up or down** button and press **OK**
14. Press **OK** when the scan is completed and then **Exit** to close the menu.

#### **To organize the channels:-**

1. Press **menu** and Select **Organizing Channels** with the **up or down** buttons and press **OK**
2. Select **Move** with the **up or down** buttons and press **OK**
3. Use the **up or down** button to highlight the channel you wish to move and press **OK**
4. Use the **up or down** button to move the channel to the desired position and press **OK**
5. Repeat step 3 and 4 for each channel you wish to move.
6. Press **exit** when completed

---

If you have another brand of satellite receiver, these are the parameters for Optus D2 that will need to be entered in to your satellite receiver.

Freq 12,706 GHz  
Symbol rate 22,500  
Pol Vertical  
FEC 3/4  
Network: Enable