

## Instructions for Tuning your receiver to the Optus D2 Satellite

### *Wavelength DSR-192*

Before you begin identify the following buttons on the remote control for the satellite receiver:

**Menu, exit, OK, the up-down and left-right buttons;  
and the red, green, yellow and blue buttons.**

Switch on the satellite receiver and TV as you normally would to watch one of the channels:-  
now you are ready to begin:-

**Note:-** When you 'select' an item on the on-screen menu it will be a different colour to the other items

#### ***To scan in the channels:-***

1. Press the **menu button** and use the left or right buttons so that the box on the left at the bottom of the screen is highlighted.
2. Use the up or down button to highlight **Manual Search** and press **OK**
3. Type in **0000**
4. Use the **up or down** buttons to select **Frequency** and type in the numbers **12707**
5. Use the **up or down** buttons to select **Symbol Rate** and type in the numbers **22500**
6. Use the **down** button to highlight **Polarization** and the **right** button to select **VER**
7. Use the **down** button to highlight **Network Search** and the right button to select **Yes**
8. Use the **down** button to highlight **FTA Only** and the right button to select **Yes**
9. Use the **down** button to highlight **Search Start** and press **OK**
10. When the search is completed press **OK**.
11. Press **Exit** and repeat to exit all menus and the TV appears on the screen.

#### ***To organize the channels:-***

1. Press **menu** and use the **left or right** buttons so that the second box from the left at the bottom of the screen is highlighted.
2. Select **Edit Channel** with the **up or down** buttons and press **OK**
3. Type in **0000**
4. Select **TV** or **All** in the **Group List** with the **left or right** and **up or down** buttons
5. Press **OK** - the highlight will move to the right column which lists all the available channels
6. To move a highlighted channel press the **Blue** button and use the up or down buttons to move the channel to its new position on the list and press **OK**
7. Press **OK** and use the **up or down** buttons to move the channel and press **OK**
8. Repeat steps 5&6 for each channel you want to move.
9. When completed press the **exit** button - wait while the data is saved.
10. Press the **exit** button to close the on-screen menus

---

If you have another brand of satellite receiver, these are the new parameters for Optus D2 that will need to be entered in to your satellite receiver.

Freq: 12,706 GHz  
Symbol rate: 22,500  
Pol: Vertical  
FEC: 3/4  
Network: Enable